Utilizing a Logic Analyzer for SDI-12 Bus Analysis

Introduction

SDI-12 Bus Overview and Applications

SDI-12 (Serial Data Interface at 1200 baud) is a low-speed serial communication protocol widely used in environmental monitoring systems, such as weather stations, hydrological monitoring, and agricultural sensing devices. The key features of the SDI-12 bus include:

1. A single-bus design supporting up to 62 sensors.
2. Low power consumption, making it suitable for long-term deployment in outdoor environments.
3. Single-wire data and power transmission, reducing wiring complexity.

As the demand for environmental data increases, SDI-12 has become a crucial standard for measurement and data transmission.

• The Role of Logic Analyzers in SDI-12 Signal Testing

A logic analyzer is a tool used for capturing and analyzing digital signals. It provides the following critical functionalities for SDI-12 bus testing and validation:

1. Accurate timing analysis: A logic analyzer can record SDI-12 digital signals at a high sampling rate, ensuring precise measurement of signal timing and voltage changes.
2. Signal decoding and data interpretation: The built-in SDI-12 decoder allows direct decoding of signals, displaying packet data requests and responses to enhance analysis efficiency.
3. Fault diagnosis: When SDI-12 communication errors occur, a logic analyzer quickly pinpoints issues such as timing errors or data corruption.

By utilizing a logic analyzer, engineers can efficiently test and validate SDI-12 buses, accelerating system development and troubleshooting.

SDI-12 Bus Communication Principles

• SDI-12 Communication Protocol Overview

SDI-12 is a digital communication protocol designed for low-power environmental sensors. It operates at a baud rate of 1200 bps using single-wire, half-duplex communication, allowing a single host (data logger) to communicate with multiple sensors.

• SDI-12 Signal Characteristics (Electrical Specifications, Timing, and Waveforms)

SDI-12 uses single-wire data transmission, with the following characteristics:

Electrical Specifications
High voltage (Logic 0): +3.5V to 5.5V
Low voltage (Logic 1): -0.5V to 1.0V
Idle state: Low voltage (Logic 1) to ensure bus stability when not in use.

Timing
Transmission rate: 1200 bps
Data format: 1 Start Bit + 7 Data Bits + 1 Even Parity Bit + 1 Stop Bit

Using a logic analyzer, signal integrity and communication stability can be verified through voltage threshold and timing analysis.



Figure 1: Typical Signal Timing Diagram.

Copyright @ZEROPLUS TECHNOLOGY CO., LTD. ALL rights reserved. Publication Release:

• Common SDI-12 Transmission Issues

Signal Attenuation
Cause: Excessive cable length or electromagnetic interference (EMI) affecting signal integrity.
Solution: Use shielded cables or shorten cable length as needed.

Timing Errors
Cause: Sensor response times not conforming to SDI-12 specifications or insufficient command interval from the host.
Solution: Use a logic analyzer to check timing and adjust the host polling interval.

Data Corruption
Cause: Sensor response errors, data loss during transmission, or incorrect parity bits.
Solution: Ensure stable device voltage and use a logic analyzer to verify SDI-12 decoding results.

By leveraging a logic analyzer, engineers can effectively analyze SDI-12 signals, ensuring stable communication and rapid issue detection.

Capturing and Analyzing SDI-12 Signals with a Logic Analyzer

• Experimental Setup and Equipment Configuration

To effectively capture and analyze SDI-12 signals, the following test environment and equipment were used:

Logic Analyzer Specifications

1. A high-sampling-rate logic analyzer, such as Zeroplus LAP-C Pro, supporting 16 channels and up to 155 channels with stacking, enabling precise signal acquisition and long-term data analysis.
2. Lossless Long Time Record mode ensures no data loss during extended recording sessions, ideal for continuous SDI-12 signal monitoring.
3. Compression and channel folding reduce storage space while improving large-scale signal capture efficiency, ensuring long-duration monitoring without losing signal details.
4. High voltage (Logic 0) adjustment: The SDI-12 signal range is +3.5V to 5.5V, and the logic analyzer can be calibrated accordingly to ensure optimal measurement accuracy.

• Signal Capture and Timing Analysis

1. Signal Capture:

Record the entire SDI-12 waveform, ensuring accurate timing and correct data transmission.
Use the logic analyzer's timing mode to analyze start and stop bit intervals, confirming compliance with SDI-12 standards.

2. Timing Analysis:

Verify data transmission intervals to ensure correct timing between host commands and sensor responses.

• SDI-12 Decoder Data Interpretation Examples

The SDI-12 decoder is capable of parsing SDI-12 signals and reading the response data.

Name	Command	Response	Note
Address Query	?!	a<CR><LF>	When a question mark (?) is used as the address character and paired with the confirmation start command (a!), the sensor will treat it as its own address (a) and

Copyright @ZEROPLUS TECHNOLOGY CO., LTD. ALL rights reserved. Publication Release:

			respond. For example, if a sensor receives ?!, it will respond with a<CR><LF> regardless of its actual address. This can be used to query the sensor's address. However, if multiple sensors are connected to the bus, all sensors will respond at the same time, which may cause bus conflicts. According to the SDI-12 specification, the sensor must support the ?! command, but it is not mandatory to support ? as a wildcard for other commands.
Acknowledge Active	a!	a<CR><LF>	This command is used to ensure that the sensor can respond to a data logger or other SDI-12 device and requires the sensor to confirm its presence on the SDI-12 bus.
Change Address	aAb!	b<CR><LF> (This command only needs to be supported if the sensor's supporting software can change the address.)	This command is used to modify the sensor address. If the sensor supports software address change, it must support this command. After the command is executed and responded, the sensor does not need to respond to other commands within the next second to ensure that there is enough time to write the new address into the non-volatile memory.
Send Identification	aI!	allccccccccmmmmmmmvvvxxx...xx<CR><LF>	This command is used to query the SDI-12 compatibility level, model and firmware version number of the sensor.
Start Measurement	aM!	atttn<CR><LF>	This command requires the sensor to start measuring, but does not immediately return the measurement results. The sensor

Copyright @ZEROPLUS TECHNOLOGY CO., LTD. ALL rights reserved. Publication Release:

			responds with the time required for measurement preparation and the number of upcoming measurements. To obtain the actual measurement data, you need to send the D0! command again.
Send Data	aD0! . . . aD9!	a<values><CR><LF> or a<values><CRC><CR><LF>	This command is used to obtain measurement data from the sensor. The D0! command needs to be sent after the M, MC, C, CC, V or HA command, and the sensor will respond with measurement data. If the data responded by D0! is incomplete, the data logger can send D1!, D2! and other commands in sequence until complete measurement values are received. The measured quantity is known from the response to the M, C or V command.

Table 1: Typical Commands and Responses.

By using a logic analyzer with SDI-12 decoding capabilities, engineers can accurately interpret each communication step, ensuring data validity and detecting anomalies.

Advantages of Using a Logic Analyzer for SDI-12 Testing

• Compared to an Oscilloscope

Logic analyzers have the following distinct advantages over oscilloscopes in SDI-12 testing：

1. Long-Term Data Capture and Storage: Lossless recording prevents missing critical signal details.
2. ASCII Packet Decoding: The SDI-12 decoder translates signals into readable ASCII text, eliminating manual interpretation.
3. Multi-Channel Capture: Simultaneously monitor multiple SDI-12 signals.
4. Flexible Trigger Conditions: Set precise triggers for SDI-12 events to efficiently pinpoint errors.

• Enhanced Signal Decoding Efficiency

1. Real-Time Decoding and Display: Instantly translates SDI-12 signals into human-readable data.
2. Error Detection: Identifies incorrect responses and communication issues.
3. Improved Test Efficiency: Reduces manual data interpretation efforts.

• Adaptability to Low-Power Environments

1. Long-Term Monitoring Capability: The logic analyzer can record data over extended periods in low-power environments without significantly impacting the power consumption of the test subject. This is particularly crucial for SDI-12 devices sensitive to power consumption.
2. No Frequent Restart Required: Compared to other test equipment, the logic analyzer can operate stably for long durations, minimizing interference with low-power devices. Additionally, it does not require frequent restarts, reducing errors and disturbances during testing.

In summary, the logic analyzer offers significant advantages in SDI-12 testing, whether for multi-channel analysis, high-precision timing measurements, long-duration recording, or adaptation to low-

Copyright @ZEROPLUS TECHNOLOGY CO., LTD. ALL rights reserved. Publication Release:

power environments. It is an ideal tool for efficient and accurate SDI-12 testing.Future Applications of Logic Analyzers in SDI-12 Testing

SDI-12 Signal Analysis and Practical Applications

• Analysis of Different SDI-12 Signal Modes (e.g., Data Requests and Response Formats)

SDI-12 data requests typically begin with a command symbol and return a response as needed. The key to analyzing data request signals lies in identifying different command formats. For example, "0!" represents a basic data request, while "0M!" indicates a monitoring mode request. The logic analyzer can accurately capture these commands and compare them with predefined decoding rules, enabling quick analysis of data requests.

Example1：Address Query

Description: The host sends an Address Query command, and the device responds with its address "0."




圖 **2: Address Query** 量測與解碼圖

Example2：Change Address

Description: The host sends a Change Address command, and the device responds with the new address "1."



Figure 3: Address Query measurement and decoding diagram.

Example3：Send Identification

Description: The host sends a Send Identification command, and the device responds with address "1," SDI-12 version "1.4," manufacturer name "SENSECAP," device model "SCO203," firmware version "2.1," and serial number or other information "35110336CO2TH."




Figure 4: Start Identificationmeasurement and decoding diagram.

Example4：Start Measurement

Description: The host sends a Start Measurement command, and the device responds with address "0." According to the device specification, "123" indicates that the measurement will be completed in 28 seconds, and "3" represents three types of data.




Figure 5: Start Measurement measurement and decoding diagram.

Example5：Send Data

Description: The host sends a Send Data command, and the device responds with address "0" and data "+187+20.14+58.38." According to the device specification, this data represents a CO2

Copyright @ZEROPLUS TECHNOLOGY CO., LTD. ALL rights reserved. Publication Release:

concentration of 187 ppm, a temperature of 20.14°C, and a humidity level of 58.38%.




Figure 6: Send Data measurement and decoding diagram.

In summary, SDI-12 signal analysis and application are not only crucial for data request and response formatting but also play a key role in signal quality evaluation and environmental monitoring implementation. By utilizing a logic analyzer, engineers can significantly improve overall system reliability and accuracy, making it an essential tool for real-world applications.

Conclusion

• Future Applications of Logic Analyzers in the SDI-12 Field

With advancements in environmental monitoring, smart agriculture, and remote data collection technologies, the applications of the SDI-12 protocol will continue to expand, playing a crucial role in increasingly complex systems. As a core tool for capturing and analyzing SDI-12 signals, logic analyzers have extensive future application prospects.

In multi-device or distributed environmental monitoring systems, logic analyzers will enable more efficient synchronized measurements, support large-scale SDI-12 network signal analysis, and play a critical role in real-time data processing and long-term data recording. This will provide enhanced support for applications requiring real-time monitoring, such as large-scale weather stations and remote water quality monitoring.

Conclusion

The application of logic analyzers in SDI-12 signal testing will continue to evolve, becoming increasingly important in future environmental monitoring and smart agriculture. With technological advancements, logic analyzers will incorporate more intelligent features, expanded capabilities, and higher efficiency in analysis. They will provide strong support for multi-device system collaboration, low-power data collection, and real-time signal processing.

Copyright @ZEROPLUS TECHNOLOGY CO., LTD. ALL rights reserved. Publication Release: